

## VESTA 4G cellular alarm system with battery or battery/external power supply



- Compact 50-zone central station via VESTA radio
- Compatible with F1 devices
- 4G connectivity (LTE)
- Sending reports via CID/SIA, Email, SMS and Push
- Configuration via App or SmartHomeSec web or via built-in keypad
- LCD display
- Up to 10 users
- Supports up to 6 PIRcam
- Built-in 100dB siren
- Powered by batteries or external battery / power supply
- Autonomy 10-12 months with external battery + 7 months with batteries
- Allows external SMA LTE antennas
- EN50131 Grade 2



Reference / Model	VESTA-068N / VESTA-068N
Stand-alone panel powered by batteries or external batteries	
Can operate with external batteries or power supplies (has a DC Jack input)	
Very low battery consumption	
MicroUSB port for quick programming with PC or even upgrades in less than 2 minutes	
Allows external SMA type LTE antennas	
GPRS/3G/4G LTE communication flexibility, allowing seamless communications at remote sites	
Plug&Play with no need for Internet connection	
Battery life: 7 months, with test transmissions every 6 hours in ECO mode	
External battery life (optional): 10-16 months with 24/7 cloud connection (depending on battery type)	
No extra boards or modules required	
Up to 50 zones via radio with a range of up to 2 km between device and control panel	
Compatibility with the large catalog of more than 50 F1 devices: keypads, sirens, smoke sensors, PIR detectors, PIRCAMS, temperature sensors, door contacts, perimeter detectors, vibration sensors, etc.	

## VESTA 4G cellular alarm system with battery or battery/external power supply

Reference / Model	VESTA-068N / VESTA-068N
Up to 10 users	
1 partition	
Supports 6 indoor and outdoor PIRCAMS, allowing users and central stations to visually verify the alarm	
Supports smoke detectors and water sensors for 24-hour protection against fire damage and water leakage	
Supports temperature sensors for high and/or low temperature protection with the possibility of range configuration	
Allows full configuration from keypad and LCD display built into the control panel	
Programming of automatic arming/disarming by schedule	
Built-in 100dB siren for immediate warning, with possibility to add indoor and outdoor F1 sirens	
Extreme convenience and flexibility in event and photo communication methods to ARC (MANITOU, encrypted MANITOU, CID, SIA)	
Possibility of remote access to CRA for quarterly testing via WAKE UP command	
EN50131 Grade 2 certified	
The free SmartHomeSec app and website allows bi-directional access at any time (with external battery or source) and immediate receipt of event and alarm notifications with photos. In addition, from the installer section, you can fully configure your control panel in less than 10 minutes.	