

VESTA EasySmart Gateway





- VESTA EasySmart radio security center with advanced home automation functions
- Up to 160 devices
- 2 security areas
- Includes F1 868Mhz radio receiver, Z-Wave Plus receiver, and IP module
- Event and photo report via APP (MANITOU, encrypted MANITOU, CID, SIA, FTP, HTTP)
- Push notification via a cloud server
- Free App
- Supports indoor and outdoor PIRCAMS
- Supports DAHUA IP cameras
- Programming of up to 100 automation rules
- Compatible with Z-Wave devices from other manufacturers
- Three different arming modes
- Remote management of lights, thermostats, locks, appliances via a smartphone app and PC web browser
- Firmware upgrade capability



Reference / Model	VESTA-243 / ESGW-F1-ZW-Battery
Radio security central with advanced home automation functions	
Allows up to 160 devices	
2 security areas	
Incorporates F1 868Mhz radio receiver	
Built-in Z-Wave Plus receiver	
Built-in IP module	
Event and photo reporting via APP (MANITOU, encrypted MANITOU, CID,	SIA, FTP, HTTP)
Free APP for User/Installer	
Full programming from the WEB platform/ APP installer "SmartHomeSec	" in less than 10 minutes
Compatibility with the large catalogue of more than 50 F1 devices: keypa PIRCAMS, temperature sensors, door contacts, perimeter detectors, vibr	
Supports indoor and outdoor PIRCAMS (User can make photo requests f	from the APP)
Programming of up to 100 automationrules (e.g. automatic watering, pre calendars, auto-arming).	sence simulation, control of any device by



VESTA EasySmart Gateway

Reference / Model	VESTA-243 / ESGW-F1-ZW-Battery
Compatible with Z-Wave devices from other manufacturers	
Allows WiFi connectivity by using WIFI dongle VESTA-064N	
Supports DAHUA IP cameras	
Logging of up to 500 events	
Remote firmware upgrade	
Power supply: 100V ~ 240V AC, 50/60Hz (5V DC /1A adapter included)	
Built-in battery backup with up to 10 hours of battery life	
Operating temperature of -10°C ~ +45°C	
Relative humidity up to 85% (non-condensing)	
Dimensions: 114 x 77 x 33 mm	