

VESTA-047NNZ-SF1

PKB1HSGWM8B4GSL02



IP + 4G home security center for 640 wireless zones

SF1



GRADE 2

4G



WORKS WITH
amazon alexa



WORKS WITH
Google Home

- VESTA home security center
- 640 wireless zones
- 240 users, 8 partitions
- Supports RF 868-F1 devices (up to 2 km)
- Compatible with PIRCAMS HD and SF1 bidirectional audio
- TCP/IP and 4G connectivity (optional WiFi pin)
- Integral solution with remote management
- Domotics and live supervision
- Sending reports via CID/SIA, Email, SMS and Push
- iOS and Android App and web browser
- Compatible with Google Home and Alexa
- EN50131 Grade 2



Reference / Model

VESTA-047NNZ-SF1 / PKB1HSGWM8B4GSL02

640 radio zones

240 users

8 partitions

TCP/IP and 4G communication (optional WiFi pin)

Incorporates 4G module

Supports RF 868-F1 devices

Supports HD streaming devices (PIRCAMS) and SF1 two-way audio

Reporting methods: CID/SIA, Email, SMS, Push Notification

Programming methods: Web and App

Live visual verification

Home automation

Energy management

24/7 emergency monitoring

VESTA-047NNZ-SF1

PKB1HSGWM8B4GSL02



IP + 4G home security center for 640 wireless zones

Reference / Model	VESTA-047NNZ-SF1 / PKB1HSGWM8B4GSL02
Remote management	
Built-in siren	
RF Frequency: 868MHz	
Power supply: 12V, 1A	
Includes Mini USB quick connector for external organic battery connection	
Operating temperature from -10°C ~ +45°C	
Relative humidity: Up to 85% (non-condensing)	
Dimensions: 140 (W) x 150 (H) x 42 mm	
EN50131 Grade 2 certified, Environmental Class II	
VESTA radio control panel is compatible with Google Home and Alexa	
Integration with Z-Wave automatic devices from Aeotec or Fibaro (Fibaro Dimmer 2, Roller Shutter 3, Smart Module, Single Switch 2) via not included dongle module VESTA-240 (ZW-DONGLE)	