

VESTA tilt sensor for garage

- VESTA tilt sensor for garage
- It **requires a VESTA-220 controller** (GDC-3)
- Alerts the system to inclinations from 35° to 55°
- Anti-tamper tamper
- Operates with 1 CR123A 3V lithium battery
- Battery life of 10 years
- Compact and stylish design

Important note: This device **does not have stand-alone operation**, a VESTA-220 (GDC-3) garage door controller is required to work properly with a VESTA control panel.



Reference / Model	VESTA-402 / TILT-GDC3-F1
Garage Door Tilt Sensor	
Designed to mount on up-and-over doors and report door status as open, closed, or moving	
Ability to integrate with VESTA-220 Garage Door Control (GDC-3)	
Tamper protection for tamper detection	
Wireless and easy to install	
Ideal for residential and commercial use	
RF Frequency: 868MHz	
Tilt angles:	
Door open: ≤35°.	
Door in motion: 35° ~ 55	
Door closed: ≥55°.	
Power supply: 1 x 3V CR123A lithium battery	
Battery life up to 8 years	
Operating temperature of -10°C ~ +45°C	

VESTA tilt sensor for garage

Reference / Model	VESTA-402 / TILT-GDC3-F1
Relative humidity up to 85% (non-condensing)	
Dimensions: 31 (W) x 86.7 (H) x 22.5 mm	