

VESTA-425

QALLMAX TOUCHPANEL-3



QALLMAX 160-zone radio touch panel



- VESTA QALLMAX home security control panel with 7" touch screen
- 160 zones via radio
- 80 users, 2 partitions
- 5MP front camera for face detection
- Supports RF 868-F1 (up to 2 km) and Z-Wave devices
- Compatible with PIRCAMS HD and SF1 bidirectional audio
- TCP/IP, WiFi and 4G LTE connectivity
- Bluetooth for contactless disarming
- Two-way voice communication
- Home automation and live monitoring
- iOS and Android App and web browser
- EN50131 Grade 2 certified.



Reference / Model

VESTA-425 / QALLMAX TOUCHPANEL-3

160 radio zones

80 users

2 partitions

7" LCD touch screen (1024x600)

5MP front camera for face detection

TCP/IP, WiFi (2.4/5GHz) and LTE communications

Built-in 4G module

Bluetooth 5.0 for contactless disarming

MicroSD card slot (not included)

Supports RF 868-F1 and Z-Wave devices

Supports HD broadcast devices (PIRCAMS) and SF1 two-way audio

Live visual verification

Home automation

QALLMAX 160-zone radio touch panel

Reference / Model	VESTA-425 / QALLMAX TOUCHPANEL-3
Energy management	
24/7 emergency monitoring	
Remote management	
Built-in 95dB siren	
Z-Wave Protocol: Z-Wave Plus 800	
RF Frequency: 868MHz	
Power supply: 5V DC, 3A, Type C	
3.7V /2500 mAh lithium polymer backup battery	
Operating Temperature -10°C ~ +45°C	
Relative humidity: Up to 85% (non-condensing)	
Dimensions: 192 (W) x 153 (H) x 31 mm	
EN50131 Grade 2 certified	