

Radio curtain PIR detector



- Radio curtain PIR detector
- Coverage up to 10 meters, 10 ° x110 °
- It can be installed on the ceiling
- Tamper proof
- Powered by 1 3V CR123A lithium battery
- 5 year battery life

**Reference / Model****VESTA-051 / IRC-29-F1****Features**

Microprocessor controlled with ADSP algorithms

Wall or ceiling mount with tamper protection

Random monitoring that verifies system integrity

Sensitivity control with temperature compensation

Battery operated for easy installation

LED works as a fault indicator and test mode

White light and noise rejection

Detection range up to 10 meters

Automatic energy saving mechanism

Meets CE requirements

Compact and low-profile with insect resistance

Fpecs

Radio curtain PIR detector

Reference / Model**VESTA-051 / IRC-29-F1**

RF frequency: 868MHz

Power: 1 3V CR123A lithium battery

5 year battery life

Detection range: 10 meters, 110 ° x10 °

Installation height: 1.4 ~ 1.6 meters

-10 ° C ~ + 45 ° C operating temperature

Relative humidity up to 85% (without condensation)

Dimensions: 56 (W) x 76 (H) x 43mm