

## VESTA temperature sensor

- VESTA temperature sensor
- Temperature detection range from -10 ° C to 45 ° C
- Provides notification when the temperature fluctuates by  $\pm 2$  ° C
- Regular transmission of temperature signals in the designated interval
- Excellent stability with high sensitivity
- Low battery detection
- LED indicator
- Slim and compact design



### Reference / Model

### VESTA-157 / TS-29-F1

Temperature sensor via radio which monitors the temperature of its environment. It detects temperatures from -10 ° C to 45 ° C, reports the temperature condition at regular intervals, and also sends a notification when the temperature fluctuates by  $\pm 2$  ° C.

Thanks to its small size, it can be installed almost anywhere, with self-adhesive mounting. In addition, it sends periodic monitoring signals to ensure the integrity of the system.

It offers a reliable and flexible way to monitor the home environment and allows users to adjust appliances accordingly for a more pleasant living space.

### specs

RF frequency: F1 868MHz  
Power supply: 1 3V CR2032 lithium battery  
Battery life of up to 1.2 years  
Sensitivity:  $\pm 1$  ° C  
-10 ° C ~ + 45 ° C operating temperature  
Operating humidity up to 85% (non-condensing)  
Dimensions: Ø40 x 14 mm