

## VESTA Carbon Monoxide Detector

- VESTA carbon monoxide detector
- Electrochemical sensor to control the level of CO
- Self-diagnosis function to ensure optimal performance
- Loud 85dB siren for audio alert
- Alarm silence button to silence nuisance alarms
- Excellent stability with high sensitivity
- Wide RF range and high speed data transmission
- Minimal power consumption with long battery life
- Two-color LED status indicator for visual notification
- Low battery detection
- Random supervisory signals to verify system integrity
- Suitable for residential and commercial premises
- Complies with EN-50291

**Reference / Model****VESTA-204 / CO-8-P2-F1****Specs**

RF frequency: 868MHz  
Measurement range: 0 ~ 450ppm  
Concentration alarm: 30 ~ 999 ppm  
Response time: <3 minutes for 300ppm concentration, 10 ~ 40 minutes for 100ppm concentration, 60 ~ 90 minutes for 50ppm concentration  
Siren sound power of 85 dB at 1 meter  
Power supply: 3 AA 1.5V alkaline batteries  
Battery life of more than 10 years  
-10 ° C ~ + 45 ° C operating temperature  
Operating humidity up to 85% (non-condensing)  
Dimensions: 130 x 100 x 41 mm