

LCD keypad with siren and NFC reader



- LCD keyboard via VESTA radio
- Backlit LCD display and keypad
- Incorporates siren and NFC tag reader
- Tamper protection
- Works with 3 lithium batteries
- EN50131 Grade 2 certified.



Reference / Model	VESTA-383 / KPT-35N-F1 (SL)
RF frequency: F1 868MHz	
32-character LCD screen displays alarm memory, event logs, fault reports or system status	
Illuminated keypad and LCD display for easy nighttime visibility	
Dual function key to activate panic, fire or medical emergency alarms	
Allows arming/disarming of the system by simply bringing an NFC tag close to it	
Integrates up to 60 NFC tags	
Built-in siren emits alarm sounds	
Audible beeps to indicate entry/exit delays and other system states	
Long battery life and power-saving feature that consumes power only when needed	
Tamper protection to prevent unauthorized removal	
Periodic supervisory signals to check system integrity	
Power supply: 3 x CR123 3V lithium batteries	
Battery life up to 5 years	

LCD keypad with siren and NFC reader

Reference / Model	VESTA-383 / KPT-35N-F1 (SL)
Low battery detection	
Operating temperature from -10°C ~ +45°C	
Operating humidity up to 85% (non-condensing)	
Easy and flexible installation with wall or desktop mounting option	
Keypad dimensions: 143 (W) x 115 (H) x 28,5 mm	
EN50131 Grade 2, Class II certified	