

VESTA-017N

RC-15-F1-2W



VESTA bidirectional radio push button



- VESTA bidirectional radio push button with 4 buttons
- Arm/disarm, start and panic
- Suitable for security and home automation
- Operates with 1 CR2032 3V lithium battery
- Battery life of 8 years
- UL1023
- EN50131 Grade 2, ClassII



Reference / Model	VESTA-017N / RC-15-F1-2W
Bidirectional communication	
Allows control of the security system	
Four buttons: Arming / Disarming / Home / Panic	
Bidirectional confirmation of actions via LEDs	
Durable, scratch-resistant buttons	
Lightweight keychain design	
Low battery detection	
Suitable for security and home automation installations	
RF Frequency: 868MHz	
Power supply: 1 CR2032 3V lithium battery	
Battery life of 8 years	
Operating temperature from -10°C ~ +45°C	
Relative humidity up to 85% (non-condensing)	

VESTA bidirectional radio push button

Reference / Model	VESTA-017N / RC-15-F1-2W
Dimensions: 65 x 38 x 15 mm	
UL1023 compliant	
EN50131 Grade 2, ClassII certified	