

4-button radio pushbutton

✓ GRADE 2

- Radio push button with 4 buttons
- Arm/disarm, start and panic
- Suitable for security and home automation
- Operates with 1 CR2032 3V lithium battery
- Battery life of 8 years
- EN50131 Grade 2, ClassII



Reference / Model	VESTA-411 / RC-16-AMX
Allows control of the security system	
Four buttons: Arming / Disarming / Home / Panic	
Durable and scratch resistant buttons	
Lightweight keychain design	
Low battery detection	
Suitable for security and home automation installations	
RF Frequency: 868MHz	
Power supply: 1 CR2032 3V lithium battery	
Battery life of 8 years	
Operating temperature from -10°C ~ +45°C	
Relative humidity up to 85% (non-condensing)	
Dimensions: 33.8 (W) x 51.08 (H) x 14.24 mm	
EN50131 Grade 2, Class II certified	